

CONTACT LEGEND










CONNECTOR TYPE	CONTACT DIA mm	GRAPHICAL SYMBOL	DIAMETER OF HOLE IN TERMINAL FOR SOLDERING CONDUCTOR (mm)
ЩР, СЩР, ЩРГ	1.5		2
ЩР, СЩР, ЩРГ	2.5		2.7
ЩР, ЩРГ	3.5		5.3
ЩР, ЩРГ	5.5		9 *
ЩР, ЩРГ	9		12 *

* CONNECTOR TYPE Y PD, QY PD HAVING PIN CONTACT PROVIDED WITH LUG TYPE TERMINATION








INSERT ARRANGEMENT






VIEW FOR PIN FROM THE TAIL END
VIEW FOR SOCKET FROM THE MATING SIDE

Connector Type	Shell Size	Contact Layout	Total Withdrawl Force Max. kgF	Maximum Current-Amp		Voltage Volts	Arbitrary No. of Contact Set	
				Per Contact	Per Connector			
ЩР	12		3.6	25	25	850	2	
2PT-A						700	1	
2PTT								
ЩР	16		4.5	50	50	850	3	
ЩРГ						840		
2PT-A						700	2	
2PTT								
ЩР	16		6	10	20	800	5	
2PT-A						700	3	
2PTT								
ЩР	20		7	25	50	850	6	
СЩР			4			840		
ЩРГ			7			700		4
2PT-A								
2PTT								
ЩР	20		9	10	30	850	6	
ЩРГ						840		
2PTT						700	38	
ЩР	20		11	25	75	850	7	
СЩР			6			840		
ЩРГ			11			700		5
2PT-A								
2PTT								

Connector Type	Shell Size	Contact Layout	Total Withdrawl Force Max. kgF	Maximum Current-Amp		Voltage Volts	Arbitrary No. of Contact Set			
				Per Contact	Per Connector					
ЩР	20		12	10	40	850	4			
ЩРГ						840				
Р						2100				
РГ						700				
2РТТ		39								
ЩР			14.5	25	100	850	8			
ЩРГ						840				
2РТ-А						700				
2РТТ						6				
ЩР			15	10	50	800	7			
ЩРГ						800				
2РТ-А						700				
2РТТ										
ЩР		18	25	125	800	10				
2РТТ					700	40				
ЩР	28		7.5	100	100	850	4			
ЩРГ						840				
2РТ-А						700				
2РТТ						8				
СЩР			8.5	25	100	850	8			
ЩР						21	10	70	850	7
ЩРГ									840	9
ЩРГ						21(25)	(25)	(175)	840	9
СЩР			14.5	25	175	850	9			
2РТ-А						25	25	700	11	
2РТТ										
ЩР		32		15	200	200	850	5		
ЩРГ	840									
2РТ-А	700									
2РТТ	12									
ЩР			29 (29)	10	80	850	2			
ЩРГ						29 (29)	25	200	700	3
2РТТ									14	
2РТТ										

Connector Type	Shell Size	Contact Layout	Total Withdraw Force Max. kgF	Maximum Current-Amp		Voltage Volts	Arbitrary No. of Contact Set
				Per Contact	Per Connector		
ЩР	32		32	10 (25)	160	850	1
ЩРГ						840	
2РТ-А						700	15
2РТТ							
СЩР		21	25	250	850	4	
ЩР	32		40	10 (25)	210	850	1
ЩРГ						700	
2РТ-А						840	16
2РТТ							
ЩР	36		26	25	275	850	13
ЩРГ						840	
2РТ-А						700	17
2РТТ							
ЩР	36		45	10 (25)	180	850	4
ЩРГ						840	
2РТ-А						700	20
2РТТ							
СЩР		31	25	337	850	5	
ЩР	40		22	100	300	850	9
ЩРГ						700	
2РТ-А							
2РТТ							
ЩР	40		49	10 (25)	190	850	2
ЩРГ						840	
2РТ-А						700	23
2РТТ							
ЩР	48		49	10 (25) (100)	490	850	1
ЩРГ						840	
2РТ-А						700	26
2РТТ							
ЩР	48		48	25 (100)	525	850	7
ЩРГ						840	
2РТ-А						700	27
2РТТ							

Connector Type	Shell Size	Contact Layout	Total Withdrawal Force Max. kgF	Maximum Current-Amp		Voltage Volts	Arbitrary No. of Contact Set		
				Per Contact	Per Connector				
ЩР	48		61	10 (25)	290	850	1		
ЩРГ						840			
2РТ-А						700		28	
2РТТ									
СЩР		42	25	400	850	2			
ЩР	48		78	10	208	850	2		
ЩРГ						840			
2РТ-А						9	234	700	29
2РТТ									
СЩР		54.5	25	400	850	3			
ЩР	55		84	10 (25) (50) (100)	448	850	1		
ЩРГ						840			
2РТ-А						9	503	700	31
2РТТ									
ЩР	55		105	10 (25) (50)	312	850	3		
ЩРГ					448	840			
2РТ-А					8 (20) (40)	512	700	3	
2РТТ									33
ЩР	55		110	10 (50)	301	850	3		
ЩРГ					840				
2РТ-А					8 (40)	344	700	34	
2РТТ									

Connector Type	Shell Size	Contact Layout	Total Withdrawal Force Max. kgF	Maximum Current-Amp		Voltage Volts	Arbitrary No. of Contact Set
				Per Contact	Per Connector		
P	55		114	10	304	2100	1
ЩР	60		147	10 (25)	525	850	2
ЩРГ						840	
2РТ-А			94.5	7 (17)	515	700	36
2РТТ							
СЩР		145	25	787,5	850	3	
ЩР	60		145	10 (25)	402	850	2
ЩРГ						840	
2РТ-А			7 (17)	399	700	37	
2РТТ							
P		141	10	329	2100	1	